

SR-4044 PCMCIA Smart Card Reader/Writer



Main Applications

Desktop

- Access Control
- Local and Network Logon
- Single Application Sign-On
- Convenience Replacement for Passwords
- 3-Factor Authentication
- Loyalty and Multi-Application Cards
- PKI (Private Key Infrastructure)
- Digital Signature
- Document Encryption
- Secure Payment for B2B and B2C

Target Markets

- Public Administration
- E-Government
- Military (CAC)
- Border Control
- E-Government
- Transportation
- Education
- Financial
- Point-of-Sales

Key Features

- PCMCIA interface for integration into notebooks
- Meets major standards
- PC/SC smart card reader
- CT-API support
- EMV 2000 Terminal level 1 approved
- CAC certified and FIPS 201 compatible

Main Part Numbers

SR-4044 PCMCIA Smart Card Reader

PCMCIA high performance PCSC/EMV smart card reader

Integrated Security Devices

SR-4044 PCMCIA Smart Card Reader/Writer

Main Part Numbers



Technical Data

Interface

PCMCIA with 16 Mbps

Smart Card Interface

Reads and writes all ISO 7816 cards

Supports T=0, T=1

I2C (S=8), SLE4044,

2-wire SLE4432/42 (S=10)

3-wire SLE4418/28 (S=9)

PC/SC Driver Support

Windows XP, 2000, 98, ME, NT 4.0

Windows CE3.0 / CE.NET (hardware dependant)

Linux

All drivers available upon request

Card Power Supply

60 mA max.

Card Connecting Unit

Approx. 100,000 insertions

Smart Card Speed:

Up to 413 Kbps (when supported by card)

Smartcard Clock Frequency:

Up to 8 MHz

Packaging Units

6100 readers per box

Warranty

2 Years

Contact

Call, fax or visit our website for more information.

ZF Electronics Corporation

11200 88th Avenue
Pleasant Prairie, WI 53158

Phone: 262.942.6500

Web: www.cherrycorp.com

E-Mail: keyboardsupport@zf.com

Fax: 262.942.6566

The manufacturer accepts no liability for errors or non-availability, and reserves the right to change specifications without prior notice.

Technical data relates to product specifications only. Features may differ from those described. Only drawings combined with product specifications shall be deemed binding.

Last Update: 2/15/10

© 2007 ZF Electronics Corporation

